



855
Purchase Order Acknowledgement
ANSI ASC X12 Version 4010

ERICO International
31700 Solon Rd.
Solon, OH 44139

Preface

Purpose and Scope

The purpose of this guide is to provide ERICO's trading partners with the necessary information to be able to send Purchase Orders via EDI to ERICO. The material presented here covers the 850 transaction set of version 004 release 010 of the ANSI ASC X12 standard. Contact ERICO for information on other standards and versions that are supported.

American National Standards Institute Accredited Standards Committee X12

ERICO uses ANSI ASC X12 standard format transaction sets for the exchange of electronic documents with its EDI trading partners. ERICO is a leader in the use of EDI in the Electrical Industry and firmly supports the use of ANSI ASC X12 standards in EDI trading partner relationships. The use of such standards cultivates a common language between trading partners and expedites EDI setup.

Mandatory Requirements

To implement electronic purchase orders, ERICO requires a list of all locations. This list should include the business name of each location and the complete address including the street, city, state, and zip. ERICO will assign an internal customer code to each location on the list that you supplied. It will be necessary to exchange electronic purchase orders to send a location code in the N104 of the ST (Ship To) that ERICO will cross reference to our internal customer code. If necessary, ERICO can supply those customer codes back to the trading partner to be sent in the N104

Pricing Lists

It may be necessary to download ERICO's pricing list(s) from our public website, if you do not have any other means of receiving our pricing data. This will help to ensure that critical data (Part number, UPC, List price, etc.) is accurate within your systems. It will also help expedite the EDI testing process. ERICO's price lists can be found at: <http://www.erico.com/priceLists.asp>. Note that there may be multiple price lists required, as ERICO carries multiple product lines.

If you have any questions about ERICO price lists, please contact Customer Service:
<http://www.erico.com/static.asp?id=14>

Communications

ERICO uses a third party Value Added Network to send and receive EDI transmissions. Below is our Network information and contact.

Network: IDX2
Network ID: 340961012 Qualifier :01
Network Contact: George Warren
Network Contact Phone Number: (925) 449-0606 x3722
Network Contact email: george.warren@activant.com

Additional Notes:

It is important to understand that ERICO's Freight Policy applies. For freight policy information, go to <http://www.erico.com/globalSearch.asp?keywords=freight>

ERICO Terms and Conditions of sale can be found at:
http://www.erico.com/public/library/Terms/TermsConds_US_1-04.pdf



Trading Partner Profile

Customer Name _____
Address _____
Main Phone Number _____

Primary EDI Contact _____
Phone Number _____
Email Address _____

Secondary Contact _____
Phone Number _____
Email Address _____

Transaction Sets

- 810 Invoice 820 Remittance Advice 850 Purchase Order
- 855 Purchase Order Acknowledgement 856 Advanced Ship Notice

Do you require a 997 Functional Acknowledgement? Yes No

ISA ID _____ Qualifier _____
GS ID _____ (if same as ISA, leave blank)

EDI Version 4010 4030 4060

Table of Contents

855	Purchase Order Acknowledgment	1
ISA	Interchange Control Header	2
GS	Functional Group Header	4
ST	Transaction Set Header	6
BAK	Beginning Segment for Purchase Order Acknowledgment	7
REF	Reference Identification	8
N1	Loop Name	9
N1	Name	10
N3	Address Information	11
N4	Geographic Location	12
PO1	Loop Baseline Item Data	13
PO1	Baseline Item Data	14
ACK	Loop Line Item Acknowledgment	16
ACK	Line Item Acknowledgment	17
CTT	Loop Transaction Totals	18
CTT	Transaction Totals	19
SE	Transaction Set Trailer	20
GE	Functional Group Trailer	21
IEA	Interchange Control Trailer	22

855

Purchase Order Acknowledgment

Functional Group=PR

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
050	REF	Reference Identification	O	>1			Must use
LOOP ID - N1					200		
300	N1	Name	O	1			Must use
320	N3	Address Information	O	2			Must use
330	N4	Geographic Location	O	1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/010L	
010	PO1	Baseline Item Data	O	1		N2/010	Must use
LOOP ID - ACK					104		
270	ACK	Line Item Acknowledgment	O	1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					1	N3/010L	
010	CTT	Transaction Totals	O	1		N3/010	Must use
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

- 2/010L PO102 is required.
- 2/010 PO102 is required.
- 3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use

Description: Code to identify the type of information in the Authorization Information

<u>Code</u>	<u>Name</u>
00	No Authorization Information Present (No Meaningful Information in I02)

ISA02	I02	Authorization Information	M	AN	10/10	Must use
-------	-----	----------------------------------	---	----	-------	----------

Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)

ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------------	---	----	-----	----------

Description: Code to identify the type of information in the Security Information

<u>Code</u>	<u>Name</u>
00	No Security Information Present (No Meaningful Information in I04)

ISA04	I04	Security Information	M	AN	10/10	Must use
-------	-----	-----------------------------	---	----	-------	----------

Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)

ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------	---	----	-----	----------

Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified

<u>Code</u>	<u>Name</u>
01	Duns (Dun & Bradstreet)

ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
-------	-----	------------------------------	---	----	-------	----------

Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element

ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------	---	----	-----	----------

Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified

<u>Code</u>	<u>Name</u>
01	Duns (Dun & Bradstreet)

ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
-------	-----	--------------------------------	---	----	-------	----------

Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them

ISA09	I08	Interchange Date	M	DT	6/6	Must use
-------	-----	-------------------------	---	----	-----	----------

Description: Date of the interchange

ISA10	I09	Interchange Time	M	TM	4/4	Must use
-------	-----	-------------------------	---	----	-----	----------

		Description: Time of the interchange				
ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use
		Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer All valid standard codes are used.				
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
		Description: Code specifying the version number of the interchange control segments				
		<u>Code</u>		<u>Name</u>		
		00401		Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997		
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
		Description: Code sent by the sender to request an interchange acknowledgment (TA1)				
		<u>Code</u>		<u>Name</u>		
		0		No Acknowledgment Requested		
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
		Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information				
		<u>Code</u>		<u>Name</u>		
		T		Test Data		
ISA16	I15	Component Element Separator	M		1/1	Must use
		Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
		Description: Code identifying a group of application related transaction sets				
		<u>Code</u>		<u>Name</u>		
		PR		Purchase Order Acknowledgement (855)		
GS02	142	Application Sender's Code	M	AN	2/15	Must use
		Description: Code identifying party sending transmission; codes agreed to by trading partners				
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
		Description: Code identifying party receiving transmission; codes agreed to by trading partners				
GS04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				
GS05	337	Time	M	TM	4/8	Must use
		Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)				
GS06	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480				
		<u>Code</u>		<u>Name</u>		
		X		Accredited Standards Committee X12		
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
		Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed				
		<u>Code</u>		<u>Name</u>		
		004010		Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997		

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the

associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
		Description: Code uniquely identifying a Transaction Set				
		<u>Code</u>		<u>Name</u>		
		855		Purchase Order Acknowledgment		
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
		Description: Code identifying purpose of transaction set				
		<u>Code</u>		<u>Name</u>		
		00		Original		
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
		Description: Code specifying the type of acknowledgment				
		<u>Code</u>		<u>Name</u>		
		AT		Accepted		
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
		Description: Identifying number for Purchase Order assigned by the orderer/purchaser				
BAK04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

REF Reference Identification

Pos: 050	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use
Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

<u>Code</u>	<u>Name</u>
L1	Letters or Notes

REF03	352	Description	X	AN	1/80	Must use
-------	-----	-------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

Loop Name

Pos: 300 Repeat: 200
 Optional
 Loop: N1 Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
300	N1	Name	O	1		Must use
320	N3	Address Information	O	2		Must use
330	N4	Geographic Location	O	1		Must use

N1

Name

Pos: 300	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
		Description: Code identifying an organizational entity, a physical location, property or an individual				
		<u>Code</u>		<u>Name</u>		
		ST		Ship To		
N102	93	Name	X	AN	1/60	Must use
		Description: Free-form name				
N103	66	Identification Code Qualifier	X	ID	1/2	Must use
		Description: Code designating the system/method of code structure used for Identification Code (67)				
		<u>Code</u>		<u>Name</u>		
		92		Assigned by Buyer or Buyer's Agent		
N104	67	Identification Code	X	AN	2/80	Must use
		Description: Code identifying a party or other code				

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 320	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Must use
Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

N4 Geographic Location

Pos: 330	Max: 1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Must use

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Must use
		Description: Free-form text for city name				
N402	156	State or Province Code	O	ID	2/2	Must use
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Must use
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 010	Repeat: 100000
Optional	
Loop: PO1	Elements: N/A

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	O	1		Must use
270		Loop ACK	O		104	Must use

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Optional	
Loop: PO1	Elements: 9

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Must use
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	X	R	1/15	Must use
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<u>Code</u>		<u>Name</u>		
		EA		Each		
PO104	212	Unit Price	X	R	1/17	Must use
		Description: Price per unit of product, service, commodity, etc.				
PO105	639	Basis of Unit Price Code	O	ID	2/2	Must use
		Description: Code identifying the type of unit price for an item				
		<u>Code</u>		<u>Name</u>		
		HP		Price per Hundred		
		PE		Price per Each		
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>		<u>Name</u>		
		UI		U.P.C. Consumer Package Code (1-5-5)		
PO107	234	Product/Service ID	X	AN	1/48	Must use
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>		<u>Name</u>		
		BP		Buyer's Part Number		
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.

7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Line Item Acknowledgment

Pos: 270	Repeat: 104
Optional	
Loop: ACK	Elements: N/A

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
270	ACK	Line Item Acknowledgment	O	1		Must use

ACK Line Item Acknowledgment

Pos: 270	Max: 1
Detail - Optional	
Loop: ACK	Elements: 5

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use
		Description: Code specifying the action taken by the seller on a line item requested by the buyer				
		<u>Code</u>		<u>Name</u>		
		IA		Item Accepted		
		IB		Item Backordered		
ACK02	380	Quantity	X	R	1/15	Must use
		Description: Numeric value of quantity				
ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<u>Code</u>		<u>Name</u>		
		EA		Each		
ACK04	374	Date/Time Qualifier	O	ID	3/3	Must use
		Description: Code specifying type of date or time, or both date and time				
		<u>Code</u>		<u>Name</u>		
		082		Promised for Shipment (After and Including)		
ACK05	373	Date	X	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

Loop Transaction Totals

Pos: 010 Repeat: 1
 Optional
 Loop: CTT Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	O	1		Must use

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				